




www.eletromack.com.br



Contato

eletromack@uol.com.br



11 - 4024 - 1968

Consulte nossos preços

Aplicações em maquinas gráficas e em projetos para uso geral.

VARIADORES DE VOLTAGEM MONOFÁSICOS 50/60 HZ

Código	Caixa	Entrada	Saída	Ampères	Potência	Peso	Dimensões
M-1205	CX-1	12 V	0-12/15 V	5,0 A	0,075 KVA	0,7 Kg	0000-0075-0050
M-2505	CX-1	24 V	0-24/30 V	2,5 A	0,075 KVA	0,7 Kg	0000-0075-0050
M-3310	CX-2	33 V	0-33/43 V	10,0 A	0,430 KVA	2,5 Kg	0145-0130-0085
M-4225	CX-1	42 V	0-42/54 V	2,5 A	0,105 KVA	1,0 Kg	0000-0075-0065
M-4245	CX-1	42 V	0-42/54 V	4,5 A	0,240 KVA	1,0 Kg	0000-0075-0065
M-4210	CX-2	42 V	0-42/55 V	10,0 A	0,550 KVA	2,5 Kg	0145-0130-0085
M-4503	CX-1	45 V	0-45/54 V	4,0 A	0,210 KVA	0,7 Kg	0000-0075-0052

VARIADORES DE VOLTAGEM MONOFÁSICOS 110 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampères	Potência	Peso	Dimensões
M-1401	CX-1	110 V	0-110/140 V	1,7 A	0,240 KVA	1,0 Kg	0000-0075-0065
M-1102	CX-1	110 V	0-110 V	2,0 A	0,220 KVA	0,8 Kg	0000-0075-0052
M-1402	CX-1	110 V	0-110/140 V	2,0 A	0,280 KVA	1,3 Kg	0000-0085-0065
M-1403	CX-1	110 V	0-110/140 V	3,0 A	0,420 KVA	1,8 Kg	0000-0085-0082
M-1404	CX-2	110 V	0-110/140 V	4,0 A	0,560 KVA	2,5 Kg	0145-0130-0085
M-1407	CX-2	110 V	0-110/140 V	7,0 A	0,980 KVA	3,2 Kg	0145-0130-0100
M-1410	CX-2	110 V	0-110/140 V	10,0 A	1,400 KVA	4,0 Kg	0145-0130-0110
M-1415	CX-3	110 V	0-110/140 V	15,0 A	2,100 KVA	6,3 Kg	0175-0150-0120
M-1420	CX-C1	110 V	0-110/140 V	20,0 A	2,800 KVA	8,2Kg	0215-0195-0135
M-1425	CX-C1	110 V	0-110/140 V	25,0 A	3,500 KVA	12,5 Kg	0250-0200-0130
M-1430	CX-A1	110 V	0-110/140 V	30,0 A	4,200 KVA	17,0 Kg	0330-0310-0120
M-1437	CX-A1	110 V	0-110/140 V	37,0 A	5,180 KVA	24,0 Kg	0330-0310-0140
M-1450	CX-B1	110 V	0-110/140 V	50,0 A	7,000 KVA	28,0 Kg	0360-0340-0150
M-1460-2P	CX-A2	110 V	0-110/140 V	60,0 A	8,400 KVA	34,0 Kg	0330-0310-0240
M-1474-2P	CX-A2	110 V	0-110/140 V	74,0 A	10,360 KVA	48,0 Kg	0330-0310-0280
M-1490-3P	CX-A3	110 V	0-110/140 V	90,0 A	12,600 KVA	51,0 Kg	0330-0310-0240
M-14100-2P	CX-B2	110 V	0-110/140 V	100,0 A	14,000 KVA	56,0 Kg	0360-0340-0300
M-14111-3P	CX-A3	110 V	0-110/140 V	111,0 A	15,400 KVA	72,0 Kg	0330-0310-0420
M-14150-3P	CX-B3	110 V	0-110/140 V	150,0 A	21,000 KVA	84,0 Kg	0360-0340-0450
M-14200-4P	CX-B4	110 V	0-110/140 V	200,0 A	28,000 KVA	115,0 Kg	0360-0340-0600
M-14250-5P	CX-B5	110 V	0-110/140 V	250,0 A	35,000 KVA	140,0 Kg	0360-0340-0750
M-14300-6P	CX-B6	110 V	0-110/140 V	300,0 A	42,000 KVA	170,0 Kg	0360-0340-0900
M-14350-7P	CX-B7	110 V	0-110/140 V	350,0 A	49,000 KVA	200,0 Kg	0360-0340-1050

VARIADORES DE VOLTAGEM MONOFÁSICOS 220 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampères	Potência	Peso	Dimensões
M-2400	CX-1	220 V	0-220 V	0,7 A	0,160 KVA	1,0 Kg	0000-0075-0065
M-2401	CX-1	220 V	0-220 V	1,0 A	0,220 KVA	1,3 Kg	0000-0085-0065
M-2402	CX-1	220 V	0-220/240 V	2,0 A	0,480 KVA	1,8 Kg	0000-0085-0082
M-2403	CX-2	220 V	0-220/240 V	3,0 A	0,720 KVA	3,2 Kg	0145-0130-0100
M-2405	CX-2	220 V	0-220/240 V	5,0 A	1,200 KVA	4,0 Kg	0145-0130-0110
M-2407	CX-3	220 V	0-220/240 V	7,5 A	1,800 KVA	6,3 Kg	0175-0150-0120
M-2412	CX-C1	220 V	0-220/240 V	12,0 A	2,880 KVA	8,2 Kg	0215-0195-0135
M-2415	CX-C1	220 V	0-220/240 V	15,0 A	3,600 KVA	12,5 Kg	0250-0200-0130
M-2420-1P	CX-A1	220 V	0-220/240 V	20,0 A	4,800 KVA	17,0 Kg	0330-0310-0120
M-2425-1P	CX-A1	220 V	0-220/240 V	25,0 A	6,000 KVA	24,0 Kg	0330-0310-0140
M-2432-1P	CX-B1	220 V	0-220/240 V	32,0 A	7,680 KVA	28,0 Kg	0360-0340-0150
M-2440-2P	CX-A2	220 V	0-220/240 V	40,0 A	9,600 KVA	34,0 Kg	0330-0310-0240
M-2450-2P	CX-A2	220 V	0-220/240 V	50,0 A	12,000 KVA	48,0 Kg	0330-0310-0280
M-2460-3P	CX-A3	220 V	0-220/240 V	60,0 A	14,400 KVA	51,0 Kg	0330-0310-0360
M-2464-2P	CX-B2	220 V	0-220/240 V	64,0 A	15,360 KVA	56,0 Kg	0360-0340-0300
M-2475-3P	CX-A3	220 V	0-220/240 V	75,0 A	18,000 KVA	72,0 Kg	0330-0310-0450
M-2496-3P	CX-B3	220 V	0-220/240 V	96,0 A	23,040 KVA	84,0 Kg	0330-0310-0450
M-24128-4P	CX-B4	220 V	0-220/240 V	128,0 A	30,720 KVA	115,0 Kg	0360-0340-0600
M-24160-5P	CX-B5	220 V	0-220/240 V	160,0 A	38,440 KVA	140,0 Kg	0360-0340-0750
M-24192-6P	CX-B6	220 V	0-220/240 V	192,0 A	46,080 KVA	170,0 Kg	0360-0340-0900
M-24224-7P	CX-B7	220 V	0-220/240 V	224,0 A	53,760 KVA	200,0 Kg	0360-0340-1050

VARIADORES DE VOLTAGEM MONOFÁSICOS 380 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampères	Potência	Peso	Dimensões
M-3803	CX-2	380 V	0-380/420 V	1,5 A	0,630 KVA	3,2 Kg	0145-0130-0100
M-3805	CX-2	380 V	0-380/420 V	2,5 A	1,050 KVA	4,0 Kg	0145-0130-0110
M-3807	CX-3	380 V	0-380/420 V	3,5 A	1,470 KVA	6,3 Kg	0175-0150-0120
M-3810	CX-C1	380 V	0-380/420 V	5,0 A	2,100 KVA	10,0 Kg	0250-0200-0120
M-3812	CX-A1	380 V	0-380/420 V	12,5 A	5,250 KVA	24,0 Kg	0330-0310-0140
M-3815	CX-C1	380 V	0-380/420 V	7,5 A	3,150 KVA	12,5 Kg	0250-0200-0130
M-3816-1P	CX-B1	380 V	0-380/420 V	16,0 A	6,720 KVA	28,0 Kg	0360-0340-0150
M-3820-2P	CX-A2	380 V	0-380/420 V	20,0 A	8,400 KVA	34,0 Kg	0330-0310-0300
M-3825-2P	CX-A2	380 V	0-380/420 V	25,0 A	10,500 KVA	48,0 Kg	0330-0310-0300
M-3830-3P	CX-A3	380 V	0-380/420 V	30,0 A	12,600 KVA	51,0 Kg	0330-0310-0450
M-3832-2P	CX-B2	380 V	0-380/420 V	32,0 A	13,440 KVA	56,0 Kg	0360-0340-0300
M-3837-3P	CX-A3	380 V	0-380/420 V	37,5 A	15,750 KVA	72,0 Kg	0330-0310-0450
M-3848-3P	CX-B3	380 V	0-380/420 V	48,0 A	20,160 KVA	84,0 Kg	0360-0460-0450
M-3864-4P	CX-B4	380 V	0-380/420 V	64,0 A	26,880 KVA	115,0 Kg	0360-0340-0600
M-3880-5P	CX-B5	380 V	0-380/420 V	80,0 A	33,600 KVA	140,0 Kg	0360-0340-0750
M-3896-6P	CX-B6	380 V	0-380/420 V	96,0 A	40,320 KVA	170,0 Kg	0360-0340-0900
M-38112-7P	CX-B7	380 V	0-380/420 V	112,0 A	47,040 KVA	200,0 Kg	0360-0340-1050

VARIADORES DE VOLTAGEM MONOFÁSICOS 440 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampères	Potência	Peso	Dimensões
M-4403	CX-2	440 V	0-440/480 V	1,5 A	0,720 KVA	3,2 Kg	0145-0130-0100
M-4405	CX-2	440 V	0-440/480 V	2,5 A	1,540 KVA	4,0 Kg	0145-0130-0110
M-4407	CX-3	440 V	0-440/480 V	3,5 A	1,680 KVA	6,3 Kg	0175-0150-0120
M-4410	CX-C1	440 V	0-440/480 V	5,5 A	2,640 KVA	10,0 Kg	0250-0200-0120
M-4410-1P	CX-A1	440 V	0-440/480 V	10,0 A	4,800 KVA	17,0 Kg	0330-0310-0120
M-4412-1P	CX-A1	440 V	0-440/480 V	12,5 A	5,250 KVA	24,0 Kg	0330-0310-0140
M-4415	CX-C1	440 V	0-440/480 V	7,5 A	3,600 KVA	12,5 Kg	0250-0200-0130
M-4416	CX-B1	440 V	0-440/480 V	16,0 A	7,680 KVA	28,0 Kg	0360-0340-0150

M-4420-2P	CX-A2	440 V	0-440/480 V	20,0 A	9,600 KVA	34,0 Kg	0330-0310-0300
M-4425-2P	CX-A2	440 V	0-440/480 V	25,0 A	12,000 KVA	48,0 Kg	0330-0310-0300
M-4430-3P	CX-A3	440 V	0-440/480 V	30,0 A	14,400 KVA	51,0 Kg	0330-0310-0450
M-4432-2P	CX-B2	440 V	0-440/480 V	32,0 A	15,360 KVA	56,0 Kg	0360-0340-0300
M-4437-3P	CX-A3	440 V	0-440/480 V	37,5 A	18,500 KVA	72,0 Kg	0330-0310-0450
M-4448-3P	CX-B3	440 V	0-440/480 V	48,0 A	23,040 KVA	84,0 Kg	0360-0340-0450
M-4464-4P	CX-B4	440 V	0-440/480 V	64,0 A	30,720 KVA	115,0 Kg	0360-0360-0600
M-4480-5P	CX-B5	440 V	0-440/480 V	80,0 A	38,400 KVA	140,0 Kg	0360-0340-0750
M-4496-6P	CX-B6	440 V	0-440/480 V	96,0 A	46,080 KVA	170,0 Kg	0360-0340-0900
M-44112-7P	CX-B7	440 V	0-440/480 V	112,0 A	53,760 KVA	200,0 Kg	0360-0340-1050

VARIADORES DE VOLTAGEM TRIFÁSICOS 220 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampéres	Potência	Peso	Dimensões
T-3401	CX-T1	220 V	0-220/240 V	1,7 A	0,647 KVA	3,6 Kg	0100-0115-0245
T-3402	CX-T1	220 V	0-220/240 V	2,0 A	0,831 KVA	4,3 Kg	0100-0115-0245
T-3403	CX-T1	220 V	0-220/240 V	3,0 A	1,247 KVA	6,0 Kg	0100-0115-0290
T-3404	CX-T2	220 V	0-220/240 V	4,0 A	1,663 KVA	8,0 Kg	0130-0135-0290
T-3407	CX-T2	220 V	0-220/240 V	7,0 A	2,910 KVA	10,0 Kg	0130-0135-0310
T-3410	CX-T2	220 V	0-220/240 V	10,0 A	4,147 KVA	12,5 Kg	0130-0135-0370
T-3415	CX-T3	220 V	0-220/240 V	15,0 A	6,235 KVA	19,5 Kg	0150-0165-0380
T-3420	CX-C3	220 V	0-220/240 V	20,0 A	8,314 KVA	35,0 Kg	0240-0210-0500
T-3425	CX-C3	220 V	0-220/240 V	25,0 A	10,392 KVA	45,0 Kg	0250-0200-0450
T-3430	CX-A3	220 V	0-220/240 V	30,0 A	12,470 KVA	60,0 Kg	0330-0310-0450
T-3437	CX-A3	220 V	0-220/240 V	37,0 A	15,380 KVA	75,0 Kg	0330-0310-0450
T-3450	CX-B3	220 V	0-220/240 V	50,0 A	20,785 KVA	85,0 Kg	0360-0340-0450
T-3474-2PF	CX-A6	220 V	0-220/240 V	74,0 A	30,764 KVA	160,0 Kg	0330-0310-0900
T-34100-2PF	CX-B6	220 V	0-220/240 V	100,0 A	41,569 KVA	180,0 Kg	0360-0340-0900

VARIADORES DE VOLTAGEM TRIFÁSICOS 380 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampéres	Potência	Peso	Dimensões
T-3800	CX-T1	380 V	0-380/420 V	0,7 A	0,460 KVA	3,6 Kg	0100-0115-0245
T-3801	CX-T1	380 V	0-380/420 V	1,0 A	0,658 KVA	4,3 Kg	0100-0115-0245
T-3802	CX-T1	380 V	0-380/420 V	2,0 A	1,445 KVA	6,0 Kg	0100-0115-0290
T-3803	CX-T2	380 V	0-380/420 V	3,0 A	2,182 KVA	10,0 Kg	0130-0135-0290
T-3805	CX-T2	380 V	0-380/420 V	5,0 A	3,637 KVA	12,5 Kg	0130-0135-0370
T-3807	CX-T3	380 V	0-380/420 V	7,5 A	5,456 KVA	19,5 Kg	0150-0165-0380
T-3812	CX-C3	380 V	0-380/420 V	12,0 A	8,720 KVA	35,0 Kg	0240-0210-0500
T-3815	CX-C3	380 V	0-380/420 V	15,0 A	10,912 KVA	45,0 Kg	0250-0200-0450
T-3820	CX-A3	380 V	0-380/420 V	20,0 A	14,549 KVA	60,0 Kg	0330-0310-0450
T-3825	CX-A3	380 V	0-380/420 V	25,0 A	18,187 KVA	75,0 Kg	0330-0310-0450
T-3832	CX-B3	380 V	0-380/420 V	32,0 A	23,279 KVA	85,0 Kg	0360-0340-0450
T-3850	CX-A3	380 V	0-380/420 V	50,0 A	36,373 KVA	160,0 Kg	0330-0310-0450
T-3864-2PF	CX-B6	380 V	0-380/420 V	64,0 A	46,557 KVA	180,0 Kg	0360-0340-0900

VARIADORES DE VOLTAGEM TRIFÁSICOS 440 V 50/60 HZ

Código	Caixa	Entrada	Saída	Ampéres	Potência	Peso	Dimensões
T-4400	CX-T1	440 V	0-440/480 V	0,7 A	0,533 KVA	3,6 Kg	0100-0115-0245
T-4401	CX-T1	440 V	0-440/480 V	1,0 A	0,762 KVA	4,3 Kg	0100-0115-0245
T-4402	CX-T1	440 V	0-440/480 V	2,0 A	1,524 KVA	6,0 Kg	0100-0115-0290
T-4403	CX-T2	440 V	0-440/480 V	3,0 A	2,494 KVA	10,0 Kg	0130-0135-0310
T-4405	CX-T2	440 V	0-440/480 V	5,0 A	4,157 KVA	12,5 Kg	0130-0135-0370
T-4407	CX-T3	440 V	0-440/480 V	7,5 A	6,235 KVA	19,5 Kg	0150-0165-0380
T-4412	CX-C3	440 V	0-440/480 V	12,0 A	9,960 KVA	35,0 Kg	0240-0210-0500
T-4415	CX-C3	440 V	0-440/480 V	15,0 A	12,471 KVA	45,0 Kg	0250-0280-0420
T-4420	CX-A3	440 V	0-440/480 V	20,0 A	16,628 KVA	60,0 Kg	0270-0300-0410
T-4425	CX-A3	440 V	0-440/480 V	25,0 A	20,787 KVA	75,0 Kg	0270-0300-0460

T-4432	CX-B3	440 V	0-440/480 V	32,0 A	26,604 KVA	85,0 Kg	0340-0340-0460
T-4450-2PF	CX-A6	440 V	0-440/480 V	50,0 A	41,560 KVA	160,0 Kg	0330-0310-0950
T-4464-2PF	CX-B6	440 V	0-440/480 V	64,0 A	52,208 KVA	180,0 Kg	0360-0340-0950